


# Power Supply Units CQM1-IPS01/IPS02

The Analog Input and Output Units require a Power Supply Unit. There are two kinds of Power Supply Units (i.e., a Power Supply Unit connecting to a single Analog Unit and the other one connecting to two Analog Units).



## Specifications

Item	Specification	Internal current consumption
CQM1-IPS01	Connecting to a single Analog Unit.	5 V DC 420 mA max.
CQM1-IPS02	Connecting to two Analog Units.	5 V DC 950 mA max.

**Note:** The CQM1-IPS02 connects to a maximum of two Analog Input Units. A single Analog Input Unit and single Analog Output Unit can be connected to the CQM1-IPS02 Power Supply Unit. Two Analog Output Units cannot be connected to the CQM1-IPS02 Power Supply Unit. When using two Analog Output Units, prepare two CQM1-IPS01 Power Supply Units.

## System Configuration Example

